

USER MANUAL OF **KS-1 TOYOTA SMART KEY** SIMULATOR

SHENZHEN XTOOLTECH CO., LTD







(E) SHENZHEN XTOOLTECH CO., LTD

1.Select: Immobilization-> TOYOTA-> All smart key lost



2. Select "Read immobilizer data" to read vehicle immobilizer data

< D	All smart key lost	
Read immobilizer data	Generate emulated key	Add key
Erase key	Force upgrade of emulated key	Help
<u>`</u> ⊂) ←		a c



3. According to the prompt, please press car's START button to read the data.

< _D		
Read immobilizer data	Generate emulated key	Add key
	Read immobilizer data	
Erase key	Press the start button once	Heip
	OK	
		s" o

It will show the completion ratio of the read data as below:



XTOOL

4. After reading the data, please save the data and name the saved file



After saving, the saved information will be shown as below:



XTOOL

5. When generating KS-1Toyota simulator key, please connect KC100 or KC501first (Please noticed the device m ust be connected to the network). Click "Generate emulated key" button.



6. And then click OK button to select the file saved in the previous step.

< 9	All smar	t key lost		
Read immobilizer dat	a Generate er	mulated key	Add key	
Erase key	Please select the backup		e Help	
	is no backup, please operate the 'Back immobilizer data' first			
	ОК	Cancel		
€	Ĵ	Ω Ω	r an	





7. After the document selection is completed, the screen will display the current key type, please click Yes or No button to confirm whether it is correct.





8. After confirmation, the system will upload data to Xtool server for data verification and calculation.





9. After verification, it will activate KC100 or KC501.



10. Please put the KS-1 simulator card into the KC100's or KC501's slot and follow the instructions to complete the next operation.





11. Please click Yes to the next step. (This operation will make device bound with KS-1 Toyota simulator card)



12. Binding succeed.





13. After the binding is successful, the simulator key is generating.



14. Generated successfully.





15. After generating the simulation key successfully, select "Add key" to do add keys.



16. Please follow prompts for relevant operations.

< 1	All smart key lost	
Read immobilizer data	Generate emulated key	Add key
Erase key Please attach the generated	Force upgrade emulated key	Help e start button and hear a beep
⊡ ⇔		⇒) <u>s</u> ∈.

XTOOL



XTOOL

17. The device will prompt Programming success.





Χτυσί

USER MANUAL OF **KS-1 TOYOTA SMART KEY** SIMULATOR

STEP BY STEP PROCESS



SHENZHEN XTOOLTECH CO., LTD



www.xtooltech.com